FH*A High-pass filter

Features

- Co-axis structure, small dimensions and easy to install.
- Low loss, highly efficient filter for rejecting return hum and interference from the dual system
- 11dB RF shielded.
- Wideband, low insertion loss and high reliability.

Model Number System

FH □□ A

- □□ — Design serial number
- □□ — Starting frequency

Specification

Item				Unit
Frequency range	5～65(30,42)	85(47,54) ～100	100～862	MHz
Insertion loss	≥45	≤0.8	≤0.5	dB
Return loss	-	≥16	≥16	dB
Dimension		19×39		mm
Weight		21		g

Shanghai Broadcast & TV Tech. Res. Inst. Co., Ltd. *Address: 6F, Building 51, 461 Hong Cao Rd, Shanghai*
Post Code: 200233
Website：www.dibosh.com Tel: +86-21-5426 2355 Fax: +86-21-5426 1178